



Date: 2020-04-15

Description								
VFD-MS300, 2HP, 1.5kw, (HD 7.5A), 1 Ø 230VAC, 1500Hz, (V/Hz, SVC), IP20, Frame C1								
Manufacturer	Heavy Duty Output Rating		Normal Duty Output Rating		Light Duty Output Rating		Single Phase Duty Rating	
Delta Electronics	HD Input Amps Rating	15,8	ND Input Amps Rating	-	LD Input Amps Rating	-	1 Ø Input Amps Rating	-
	Rated HP	Rated Amps	HP	Rated Amps	HP	Rated Amps	HP	Amps
	-	-	-	-	-	-	2,0	9,0
	Max. HP	Max. Amps	Max. HP	Max. Amps	Max. HP	Max. Amps	Max. HP	Max. Amps
Max. Capacity	-	-	-	-	-	-	2,0	9,0
Line Reactor	Heavy Duty		Normal Duty		Light Duty		1 Ø Phase	
	Line	Load	Line	Load	Line	Load	Line	Load
Model	-	KDRMA27L1	-	-	-	-	KDRB25H	KDRMA27L1
HP Rating	-	2,00	0,0	-	0,00	-	5,00	2,00
Max Amps	-	10,0	-	-	-	-	17,0	10,0
Inductance uH	-	1350	-	-	-	-	1030	1350
Nema 1 Encl.Size	-	C1	-	-	-	-	C1	C1
Motor Models Compatible	Heavy Duty		Normal Duty		Light Duty		1 Ø Phase	
	Model	HP	Model	HP	Model	HP	Model	HP
	MQP-12	2	MQP-17	3	-	-	MQP-12	2
	FLA	6,2	FLA	7,6	FLA	-	FLA	6,2
VFD Dimensions	Width (mm)	Width (in.)	Height (mm)	Height (in.)	Depth (mm)	Depth (in)	Wgt (Kg)	Wgt (lbs)
	87	3,42519	157	6,18109	152	5,98424	1,2	2,87742
	Input Voltage	Input Frequency	Input Phase	Enclosure	Control Method	V/Hz, Sensorless Vector, PM Motor Control		
	200 ~ 240VAC (± 10%)	50/60Hz (±5%)	1	NEMA1 Optional				
Regulated Output Voltage	Efficiency	Motor Current Protection Range	Stall Prevention Level HD	Stall Prevention Level ND	Stall Prevention Level LD	Carrier Frequency	Accel / Decel Time	Default Rating
0.0 ~ 255.0Vac	≥97%	0.75 ~ 9.0 A	0 ~ 200%	-	-	2 ~ 15kHz	0.00 ~ 600.00	Heavy Duty
Over Torque Level	DC Injection	Braking Chopper	Equivalent Braking Resistor Circuit	Minimum Braking Resistance Value	Starting Torque @			
					V/Hz	SVC	VC+PG	
10 ~ 250%	0 ~ 100.0 %	Builitn	200W 91Ω	47.5 Ω	10 ~ 200% @ 3.0Hz	-	-	
Analog Inputs			Analog Outputs			Keypad	Fault Record	Reel Time Stamp
AVI	ACI	AUI	AFM1	AFM2	DFM			
0 ~ 10vdc or -10 ~ +10vdc	0/4 ~ 20ma or 0 ~ 10vdc	-	0/4 ~ 20ma or 0 ~ 10vdc	-	-			
Digital Inputs					Signal mode			
Dedicated		Safe Torque Off	Programmable	Control Voltage				
STO1, STO2		Yes	7	24vdc	Sink (NPN) / Source (PNP)			
Digital Outputs			Built in Controllers					
DO1	DO2	DO3	DO4	Preset speeds	Process Control	PLC	PID	Position
1NO/NC Form C relay, ≤ 240VAC, ≤ 24vdc	Optocoupler NPN ≤ 48vdc	Optocoupler NPN ≤ 48vdc	-	15	No	2K Steps	Yes	No
Communication				Built In Protocol 1	Built In Protocol 2	Built In Protocol 3		
Comm Port 1	Comm Port 2	Comm port 3	Comm port 4					
USB type B	RJ45 (RS-485) / SG+, SG-	-	-	Modbus ACSII	Modbus RTU	-		
Options								
Option 1	KPC-CC01	Standard keypad shipped with C2000 series. Also compatible, MS-300 & MH-300.						
Option 2	MKC-KPPK	VFD-C2000, Keypad Remote Panel Adapter, IP66						
Option 3	MKM-EPC	VFD-MH/MS300, EMC Shielded Cable Earthing Plate, Frame C						
Option 4	-	-						
Option 5	KPC-CE01	VFD-C2000, LED English Keypad for C2000						
Option 6	MKM-CBC	VFD-MH/MS300, NEMA1 conduit box frame C						
Option 7	CMM-COP01	VFD-MH/MS300, CANopen Communication Card						
Option 8	CMM-DN01	VFD-MH/MS300, DeviceNet Communication Card						
Option 9	CMM-EIP01	VFD-MH/MS300, EtherNet/IP Communication Card						
Option 10	CMM-EC01	VFD-MH300, EtherCAT Communication Card						
Option 11	CMM-MOD01	VFD-MH/MS300, Modbus TCP Communication Card						
Option 12	CMM-PD01	VFD-MH/MS300, Profibus DP Communication Card						
Option 13	EMM-BPS01	VFD-MH/MS300, Back-up Power Supply card						
Option 14	MKM-DRC	VFD-MH/MS300, DIN Rail Kit, Frame C						
Option 15	EG1010A	1 meter Extension Cable for remote Keypad mounting, compatible with B, M, E, MH-300 & MS-300 series removable Keypads						
Option 16	EG2010A	2 meter Extension Cable for remote Keypad mounting, compatible with B, M, E, MH-300 & MS-300 series removable Keypads						
Option 17	EG3010A	3 meter Extension Cable for remote Keypad mounting, compatible with B, M, E, MH-300 & MS-300 series removable Keypads						
Option 18	EG5010A	5 meter Extension Cable for remote Keypad mounting, compatible with B, M, E, MH-300 & MS-300 series removable Keypads						